SIGENERGY

Sigen Power Sensor



Sigen Sensor Sub1G Kit



Sigen Power Sensor

- WiFi halow remote communication functionality (with Sigen Sensor Sub1G Kit)
- Efficient and stable data transmission up to 200m (with Sigen Sensor Sub1G Kit)
- 1% high-accuracy power detection for precise control
- LCD real-time info display, easy to operate and check
- Integrate smoothly with Sigenergy devices, no need for setup
- Top class 100A direct connection in power sensor with built-in CT
- 100ms data refresh rate, instantaneous data feed

Enjoy Green Energy

Sigen Power Sensor

Sigen Sensor [1]	TP-CT120-DH	TP-CT300-DH	TP-CT600-DH	TPX-CH [2]	Units
Power Supply					
Grid connection type		3P3W/3P4W			
AC input voltage range		173 ~ 480		100 ~ 480	Vac
Nominal AC frequency		50 / 60			Hz
Measurement Accuracy					
Voltage accuracy		0.5%			
Current accuracy		0.5%			
Power accuracy		1%			
Frequency accuracy		0.2%			
Communication					
Interface		RS485			
Baud rate		9,600			bps
Protocol		Modbus RTU			
General Data					
Dimensions (W / H / D)		72 / 94.5 / 65		72 / 100 / 65.5	mm
Weight	0.20	0.20	0.23	0.35	kg
Storage temperature range		-40 ~ 70			°C
Operating temperature range		-25 ~ 65			°C
Relative humidity range		0% ~ 90%			
Ingress protection rating		IP20			
Installation method		DIN Rail 35 mm			
CT Accessory					
Number of CT	3	3	3	-	pcs
Cable length of CT	1	1	1	-	m
Inner diameter of CT	16	24	36	-	mm
Weight of CT	0.09	0.2	0.4	-	kg
Max. operating current of CT	120	300	600	-	A
Standard Compliance					
Standard		EN 61010-1:2010, EN 61010-2-030:2010			

	Sigen Sensor Sub1G Kit	Units
Working mode	AP (master device), STA (slave device)	
Communication method	RS485 / wireless communication	
Protocol	IEEE 802.11ah	
Operating voltage	85 ~ 277	Vac
Power consumption	≤ 2	W
Operating temperature range	-25 ~ 55	°C
Dimensions (W / H / D)	18 / 118 /66	mm
Wireless frequency	868	MHz
Wireless transmission distance [3]	≤ 200	m
Installation method	DIN Rail 35 mm	

1. For more models refer to the Sigenergy website.
2. Sigen Sensor TPX-CH does not included CT, which needs to be purchased separately with the following requirements: Primary rated current In/A ≥ Measuring current, secondary rated current I0/A is 5A or 1A, accuracy ≥ 0.5, and the default CT ratio of the power sensor is 200, need to be reset according to the CT ratio.
3. Lab tests have shown a maximum horizontal range of up to 200 metres in open spaces, with shorter communication distances when walls are in the way.

Disclaimer: The information in this file is provided on an "as is" basis. To the fullest extent permitted by law, Sigenergy Technology Co., Ltd. excludes all representations and warranties relating to this file and its contents or which is or may be provided by any affiliates or any other third party, including in relation to any inaccuracies or omissions in this file.